

# **BF-TP800**

## **HYBRID PORTABLE RADIO**











#### **OVERVIEW**

TP800 is a new advanced multi-mode radio which integrates Public broadband and narrowband PMR technology to provide critical voice and data services. It brings flexible usability of public network, private network, mixed network and gateway mode, and performance advancements like split-screen, dual PTT, GPS, recording, Bluetooth, etc., to be convenient and benefit for every aspect of radio experience. Designed to meet diversified requirements, it ensures mission-critical reliability, accelerates workflows and keeps responders safe and effective.

## **HIGHLIGHTS AND BENEFITS**



#### **Multi-mode Hybrid, Flexible Communications**

A multi-mode radio works in DMR, analog and PoC (public 4G/3G/2G) mode, which could always be stay in connect, to communicate whenever and wherever.

## 010

#### **Intelligent Gateway Mode**

This smart radio provides outstanding connectivity of PMR (DMR or analog) and PoC, brings all the advantages of narrowband and broadband technologies, bridging the voice communication over different networks.



#### **Intuitive Multi-Active Split-screen**

Designed with full keypad, 1.77" transflective LCD, it offers you the choice of narrowband and broadband display up and down.



#### 5000mAh Extended Battery Life


It comes with a 14-hour smart lithium battery and a built-in PTC protection to take your communication even further.



## **APPLICATION**











## **ACCESSORIES**











## **SPECIFICATION**

	General
	VHF: 136-174MHZ
Frequency Range	UHF: 350-390MHz/ 400-480MHz/ 450-520MHz
Channels	100
Channel Spacing	12.5KHz/ 25KHz
Working Voltage	DC 3.7V
Frequency Stability	±1.5ppm
Antenna Impedance	50Ω
Battery Capacity	5000 mAh
Battery Average Working Time (5/5/90)	Public Network: 14hours PMR Network: 11 hours
Dimension(H*W*D)	123* 60* 30mm (nExcluding antenna)
Weight	300g (Excluding battery)
Network Standards	LTE-FDD: B1/B3/B5/B8 LTE-TDD: B38/B39/B40/B41 WCDMA: B1/B8 TD-SCDMA: B34/B39
Transmitter (DMR Part)	
Output Power	High power: $4.0 \pm 0.2W$ Low power: $1.0 \pm 0.2W$
4FSK Modulation	12.5KHz data only: 7K60FXD 12.5KHz data and voice: 7K60FXE
Modulation Limitation	±2.5KHz @ 12.5KHz ±5KHz @ 25KHz
Spurious Emission	-36 dBm ≤1GHz/-30 dBm ≥1GHz
Adjacent Channel Power	≤-60dB
Adio Response	+1/-3dB
Audio Distortion	3%
Receiver (DMR Part)	
Digital Sensitivity	5% BER: 0.25μV
Analog Sensitivity	0.22uV (12 dB SINAD)
Intermodulation	60dB
Adjacent Channel Selectivity	50dB
Spurious Suppression	ETSI/TIA603: 55dB
FM Noise	40dB @ 12.5kHz 45dB @ 25kHz
Frequency Response	+1/-3 dB
Audio Power	1.5W
Audio Distortion	≤5%
Conduction Radiation	3%(typical)
GPS Precision	Horizontal Accuracy ≤10m (with good signal)
Environmental Specifications	
Operating Temperature	-20℃~+65℃
Storage Temperature	-30°C~+85°C
Water Proof	IP54
Shock & Vibration	MIL-STD-810C/D/E/F

#### Fujian BelFone Communications Technology Co., Ltd

Add: A-15 Huaqiao Economic Development Zone, Luojiang, Quanzhou, Fujian, China

**Email:** overseas@belfone.com **Phone:** +86 595 28396717 **Fax:** +86 595 22771635

BelFone
Communications for Efficiency and Safety



Dedicated to increasing the efficiency and reliability of missioncritical communications, BelFone is always on the way to offer responsive, flexible and reliable products. For more information about our products and solutions, contact us or visit us at www.belfone.com.